

RMG 4015 Crack Depth Measurement

KARL DEUTSCH


RMG 4015 Principle of Measurement



The crack depth meter: RMG 4015



Delivery in a sturdy hard case



Technical literature written by Prof. Dr. V. Deutsch

You are looking for an easy-to-use instrument to measure the depth of surface cracks in metals which you have detected by e.g. Magnetic Particle Testing (MT) or Penetrant Testing (PT)? You want to evaluate the extension, the orientation or the inclination angle of the crack so you are able to make a decision on a possible rework on the specimen? Or you want to monitor the growth of a crack with increasing operation time?

Then we recommend the crack depth gauge RMG 4015

Advantages of the RMG

Since alternating current (AC) is used, the measurement takes advantage of the skin effect: The current is urged to flow close to the surface and thus follows the contour of the crack to a great extent. An additional advantage: Due to low pulsed current the required result is achieved and possible burnt contact spots on the specimen can be avoided. The small, battery-operated handheld unit com-


bines current generation, measurement technique and microprocessor-based evaluation and can be taken along conveniently to any job site.

The RMG is optimized for the use on steel, iron and austenitic material. A material specific calibration adapts the instrument to distinct electrical and magnetical properties. For this purpose the RMG offers various calibration methods: In the simplest case it is sufficient to execute a comparison measurement at a crack-free spot of the specimen. Higher precision is achieved by means of a comparison measurement at a reference notch with a depth close to the expected crack depth. A multiple point calibration over reference notches with varying depth covering the whole measuring range leads to the best results.


The crack depth gauge RMG 4015 can also be used on copper, brass, aluminium or other metallic material (however measuring range and resolution might be reduced). For difficult applications it is possible to adapt a special probe to specific requirements (on request).

Measurement Technique

The RMG uses the potential drop method with alternating current: Via two current poles located left and right to the crack a constant alternating current is passed into the workpiece. The voltage drop between two additional poles positioned left and right to the crack is proportional to the crack depth. Conditions for a reliable measurement: The electrical and magnetical properties of the material surrounding the crack are sufficiently homogenous. The width of the crack has almost no influence on the measurement (Fig. left). For a crack depth measurement of inclined cracks the frequency of the alternating current is automatically lowered so that the electric current covers a wider area in the workpiece. Depending on the position of the external current pole (positioned either left or right with respect to the crack) different voltage drops result which are used to calculate the angle α (Fig. right).



Crack depth measurement at normal cracks



Angle and depth determination of inclined cracks

Key Properties and Probes

All RMG properties at a glance

- Ideal accessory for MT or PT
- Small, battery-operated mobile instrument
- Low weight (225 g / 8 oz)
- Display of the crack depth in mm or inch
- Menu-guided operation
- Crack depth measurement also for inclined cracks in ferromagnetic material; resolution of 10° in steel is possible
- Orientation of inclined cracks determinable with special probe setup
- Robust probe design
- Easy choice of the right probe: Three standard probes are suitable for most workpieces
- Special probes for surfaces of complex shape and difficult to access crack locations

- Sturdy, exchangeable and gold plated contact pins
- Interface for printer and PC
- · Memory for measured crack depths
- Fast evaluation (1 measurement per second)
- Single and continuous measurement operation
- Wide range of accessories: Control blocks, polishing fleece, self-twisting or needle contact pins
- Technical literature "Crack depth gauging with the potential probe method" is included
- Service: Repeated acceptance checks of instrument and probes possible
- Advice and knowledge: Our specialists will be glad to support you



Crack depth measurement of an inclined crack after angle determination



Measurement of a normal crack on a small area


Standard probes (all dimensions in mm)		Specification	Order no.
2.54 ****	Ø25	Probe RMSQ 0° Square arrangement of the pins for measurement of normal cracks at difficult to access locations. Incl. 1 set of spare contact pins (standard pins)	4418.001
50 \ \frac{1}{120} \ \tag{\alpha}24		Probe RMSL 90° 90° right-angled probe with linear arrangement of contact pins for measurement of normal cracks (e.g. inside of bore holes, inside of tubes). Incl. 1 set of spare contact pins (standard pins)	4417.001
2.54 AM SEUTSCH RHILLS & ASTRON	Ø25	Probe RMSL-S 0° Linear arrangement of contact pins for measurement of inclined and normal cracks. The design of the probe allows for measurement at difficult to access locations. Incl. external magnet as 2nd current pole, cable and 1 set of spare contact pins (standard pins)	4421.001
50 \ \frac{1}{120} \ \times 24		Probe RMSL-S 90° 90° right-angled probe with linear arrangement of contact pins for measurement of inclined and normal cracks (e.g. inside of bore holes, inside of tubes). Incl. external magnet as 2nd current pole, cable and 1 set of spare contact pins (standard pins)	4420.001
2.54 ************************************	■ Ø25	Probe RMSL 0° Linear arrangement of contact pins for measurement of normal cracks. The design of the probe allows for measurement at difficult to access locations. Incl. 1 set of spare contact pins (standard pins)	4416.001
Special probes (all dimensions in mm)		Specification	Order no.
50		Special probe RMSL 90° 90° right-angled probe with linear arrangement of contact pins for measurement of normal cracks. With a special arrangement of the pins it is possible to measure cracks with a width of more than 2.54 mm (0.1 inch).	4498.004
13.5 100 1250	-1	Special probe RMSQ 90° 90° right-angled probe with square arrangement of the pins to measure particularly small, normal cracks in very narrow gaps.	4498.007
Ø10 ± 100		Special probe RMSQ 0° Square arrangement of the pins to measure normal cracks at very difficult to access locations (e.g. inside deep bore holes, grooves).	4498.010

Gladly we support you concerning the solution of your problem and can suggest an appropriate special probe if required.

2 3 1	
1	
	7499.P4015.EN.0607
	Printed in Germany 06/07 ·
	ge without notice .
	5 E · Subject to ch
	Leaflet P 401

Order no.		Order no.		Order no.
4015.003	Accessories		Software	
	RMG reference block (0-10 mm crack)	4720.002	STATWIN 2002, PC software for processing	ıg
	Charger (230 V) for inserted rechargeable batteries	2806.001	(for Windows 9x/XP/ME/2000/NT4.0)	2904.001
4418.001	Rechargeable battery set NiMH (2 x 1.2 V, size AA)	6016.001	EasyExport, PC software for data transfer	
4416.001	External charger 230 V for NiCd/NiMH batteries (4 x size AA)	6015.001	(for Windows XP/2000)	2905.001
4417.001	Matrix printer (incl. 230 V mains unit, paper roll, printer ribbon)	6010.001		
	Printer cable RMG 4015 for matrix printer 6010	1657.305	Consumption material	
	PC cable RMG 4015 for RS232C interface (PC)	1657.307	8 contact pins (standard)	4815.001
4421.001	Fitting tool to replace probe contact pins	4816.001	4 contact pins (needle)	4815.002
4420.001	Protective bag for RMG 4015	4825.001	4 contact pins (self-twisting)	4815.003
4901.001	Literature: Crack depth measurement by Prof. Dr. V. Deutsch	6607.041	Polishing fleece (5 pcs.) for control block	4820.001
			Mains/charger unit (230 V)	
			for printer 6010	6013.001
	4015.003 4418.001 4416.001 4417.001 4421.001 4420.001	4015.003 Accessories RMG reference block (0-10 mm crack) Charger (230 V) for inserted rechargeable batteries 4418.001 Rechargeable battery set NiMH (2 x 1.2 V, size AA) 4416.001 External charger 230 V for NiCd/NiMH batteries (4 x size AA) 4417.001 Matrix printer (incl. 230 V mains unit, paper roll, printer ribbon) Printer cable RMG 4015 for matrix printer 6010 PC cable RMG 4015 for RS232C interface (PC) 4421.001 Fitting tool to replace probe contact pins 4420.001 Protective bag for RMG 4015	4015.003 Accessories RMG reference block (0-10 mm crack) 4720.002 Charger (230 V) for inserted rechargeable batteries 2806.001 4418.001 Rechargeable battery set NiMH (2 x 1.2 V, size AA) 6016.001 4416.001 External charger 230 V for NiCd/NiMH batteries (4 x size AA) 6015.001 4417.001 Matrix printer (incl. 230 V mains unit, paper roll, printer ribbon) 6010.001 Printer cable RMG 4015 for matrix printer 6010 1657.305 PC cable RMG 4015 for RS232C interface (PC) 1657.307 4421.001 Fitting tool to replace probe contact pins 4816.001 4420.001 Protective bag for RMG 4015 4825.001	Accessories RMG reference block (0 – 10 mm crack) Charger (230 V) for inserted rechargeable batteries 4720.002 STATWIN 2002, PC software for processin (for Windows 9x/XP/ME/2000/NT4.0) 4418.001 Rechargeable battery set NiMH (2 x 1.2 V, size AA) 6016.001 External charger 230 V for NiCd/NiMH batteries (4 x size AA) 6015.001 Matrix printer (incl. 230 V mains unit, paper roll, printer ribbon) Printer cable RMG 4015 for matrix printer 6010 PC cable RMG 4015 for RS232C interface (PC) 1657.307 Consumption material PC cable RMG 4015 for RS232C interface (PC) 421.001 Fitting tool to replace probe contact pins 4816.001 420.001 Protective bag for RMG 4015 420.001 Literature: Crack depth measurement by Prof. Dr. V. Deutsch Mains/charger unit (230 V)







Control block and polishing fleece



STATWIN 2002 with PC cable and probe RMSQ 0°

Technical data of RMG 40)15			
Application	Depth measurement of surface cracks in electrically conducting materials			
Principle of measurement	AC electrical potential drop method			
Dimensions (W x H x D)	83 mm x 151 mm x 35 mm / 3.3 inch x 5.9 inch x 1.4 inch			
Weight	225 g / 8 oz			
Power supply	2 x 1.5 V Alkali-Manganese dry cells, size AA (mignon), alternatively 2 x 1.2 V NiCd or NiMH rechargeable batteries, size AA. Optical alarm in case of empty batteries.			
Operating time	At least 11.5 hrs with Alkali-Manganese cells.			
Data storage	A total number of approx. 3850 values can be stored in up to 300 batches. For each batch, a statistical evaluation can be printed out. This evaluation determines the minimum value, the maximum value, the average value and the standard deviation.			
Measuring range	0 mm to 99.9 mm / 0 inch to 3.9 inch for ferrous material, 0 mm to 12 mm / 0 inch to 0.5 inch for aluminium, copper, brass.			
Measurement accuracy	Depending on material and measuring range. Typical figure for two-point material correction: Ferromagnetic material 3 to 15 %, austenitic material 3 to 25 %.			
Serial interface	RS232C to KARL DEUTSCH printer or PC: 4800 bauds, 8 data bits, 1 stop bit, no parity bit. USB-adapter available.			
Environmental conditions	Operating temperature: From 0° C to 45° C, storage temperature: -20° C to 60° C with removed batteries, From 0° C to 45° C with inserted batteries (depending on battery type and brand).			

KARL DEUTSCH Prüf- und Messgerätebau GmbH + Co KG Otto-Hausmann-Ring 101 · 42115 Wuppertal · Germany Phone (+49 -202) 7192 - 0 · Fax (+49 -202) 7149 - 32 info@karldeutsch.de · www.karldeutsch.de

